

# High-Voltage Rectifier Diodes

$t_{rr}$  ①:  $I_F/I_R (=I_F)$  90% Recovery Point  
(ex.  $I_F/I_R = 100\text{mA}/100\text{mA}$  90% Recovery Point)

Division	$V_{RM}$ (kV)	Part Number	$I_F$ (AV) (mA)	$I_{FSM}$ (A)	$T_c$ (°C)	$T_{stg}$ (°C)	$V_F$ (V) max	$I_F$ (mA)	$I_R$ ( $\mu\text{A}$ )	$I_R$ (H) ( $\mu\text{A}$ )	$T_a$ (°C)	$t_{rr}$ ① ( $\mu\text{s}$ )		Mass (g)	Fig. No.	
				50Hz Half-cycle Sinewave Single Shot					$V_R = V_{RM}$ max	$V_R = V_{RM}$ max		$T_a = 100^\circ\text{C}$	$I_F/I_{FP}$ (mA)			
For General Purpose	2	SHV-02	2.0	0.3	100	-40 to +120	16	10	1	3	100	0.18	—	10/10	0.13	1
	3	SHV-03S	2.0	0.3	100	-40 to +120	16	10	1	3	100	0.18	—	10/10	0.13	
	3	SHV-03	2.0	0.5	100	-40 to +120	16	10	1	3	100	0.18	—	10/10	0.16	2
For General FBT	10	SHV-10	2.0*	0.5	100	-40 to +120	40	10	1	3	100	0.18	—	10/10	0.33	5
	12	SHV-12	2.0*	0.5	100	-40 to +120	45	10	1	3	100	0.18	—	10/10	0.33	
	14	SHV-14	2.0*	0.5	100	-40 to +120	55	10	1	3	100	0.18	—	10/10	0.33	
	16	SHV-16	2.0*	0.5	100	-40 to +120	60	10	1	3	100	0.18	—	10/10	0.33	
	20	SHV-20	2.0*	0.5	100	-40 to +120	75	10	1	3	100	0.18	—	10/10	0.33	
	24	SHV-24	2.0*	0.5	100	-40 to +120	75	10	1	3	100	0.18	—	10/10	0.33	
For High Frequency Multi-layer FBT	6	SHV-06EN	2.0*	0.5	100	-40 to +120	24	10	1	3	100	0.15	0.20	10/10	0.17	3
	8	SHV-08EN	2.0*	0.5	100	-40 to +120	30	10	1	3	100	0.15	0.20	10/10	0.17	
	10	SHV-10EN	2.0*	0.5	100	-40 to +120	38	10	1	3	100	0.15	0.20	10/10	0.20	
	12	SHV-12EN	2.0*	0.5	100	-40 to +120	45	10	1	3	100	0.15	0.20	10/10	0.20	
For Ultra-High Frequency Multi-layer FBT	8	SHV-08DN	2.0*	0.5	100	-40 to +120	30	10	1	3	100	0.15	0.20	10/10	0.17	3
	10	SHV-10DN	2.0*	0.5	100	-40 to +120	38	10	1	3	100	0.15	0.20	10/10	0.20	
	12	SHV-12DN	2.0*	0.5	100	-40 to +120	45	10	1	3	100	0.15	0.20	10/10	0.20	
For General Type Microwave Oven	9	HVR-1X-40B	350	20	60 ( $T_a$ )	-40 to +130	9	350	10	$V_Z = 9.5$ to $15\text{kV}$		—	—	—	2.5	7
For Inverter Type Microwave Oven	8	UX-F5B	350	15	60 ( $T_a$ )	-40 to +130	14	350	10	$V_Z = 8.5\text{kV min}$		0.15	—	100/100	2.5	
For Automotive Ignition Coil	2.5	SHV-05JS	30	3	—	-40 to +150	5	10	10	$V_Z = 2.6$ to $5.0$ (@ $I_Z = 100\mu\text{A}$ )				0.16	2	
	3.0	SHV-06JN	30	3	—	-40 to +150	6	10	10	$V_Z = 3.2$ to $6.0$ (@ $I_Z = 100\mu\text{A}$ )				0.17		
	4.0	SHV-08J	30	3	—	-40 to +150	8	10	10	$V_Z = 4.5$ to $8.0$ (@ $I_Z = 100\mu\text{A}$ )				0.20		
	15.0	SHV-30J	30	3	—	-40 to +150	30	10	10	$V_Z = 16.0$ to $30.0$ (@ $I_Z = 100\mu\text{A}$ )				0.33		

\* FBT High Voltage Rectifier Capacitive Load,  $T_c \leq 100^\circ\text{C}$

# High-Voltage Rectifier Diodes

Part Number	External dimensions	Marking (Cathode Mark)	
		Pattern	Color
SHV-02	<b>1</b>		White
SHV-03S			Red
SHV-03	<b>2</b>		White
SHV-05J			Red
SHV-06JN	<b>3</b>		White
SHV-06EN			White
SHV-08EN			White
SHV-08DN			Red
SHV-10EN	<b>4</b>		White
SHV-10DN			Red
SHV-12EN			White
SHV-12DN			Red
SHV-10	<b>5</b>		White
SHV-12			
SHV-14			
SHV-16			
SHV-20			
SHV-24			
SHV-30J			
HVR-1X-40B	<b>7</b>		White
UX-F5B			
SHV-08J	<b>8</b>		White

●The SHV series of diodes have been miniaturized by resin on the assumption for remolding. Measures against creeping discharge and humidity stress must be taken when using these diodes.

●The tapping specifications of the SHV series differ from ordinary diodes. (P.10)